

 File No.:
 MF-02-D

 Version:
 A

 Page:
 1/13

 Date :
 2021.01.01


1. INTRODUCTION

To fill the function gap of carbon film resistors, metal oxide film resistors or wire wound resistors SYNTON-TECH mages metal film resistors. The resistive element is a high contests of AL203 ceramic rod on which a thin film of Ni/Cr alloy is deposited by vacuum sputtering system. Then contact caps are pressed onto the ends of the rod and a helical grove cut through the film to give the required resistance value. Connecting copper wire are welded to the end caps. Finally the resistors are coated with multiple layers of insulation lacquer. **SYNTON-TECH's** MF series are suitable for all circuit applications especially tighter tolerance and low temperature coefficient are required.

2. FEATURES

- Meet American military specification MIL-R-10509F!
- Very low current noise!
- Major applications are switching power supplies, communications equipment, monitors, testing meters.

APPROVED	CHECKED	DESIGNED	REMARK	DOCUMENT NO.
Carol	May	Chen		0201010017





METAL FILM FIXED RESISTORS

 File No.:
 MF-02-D

 Version:
 A

 Page:
 3/13

 Date :
 2021.01.01

4. ELECTRICAL CHARACTERISTICS

ТҮРЕ	MF-	MF-	MF-	MF-	MF-	MF-	MF-	MF-	MF-	MF-	MF-	MF-	MF-	MF-
	12	25S	40S	33S	25	50S	60S	50	100S	100	200S	200	300S	500SS
Power Rating at 70℃	1/16W 1/8W 1/6W	1/4W	0.4W	1/3W	1/4W	1/2W	0.6W	1/2W	1W	1W	2W	2W	3W	5W
Operating Temp. Range		$-55^{\circ}\text{C} \sim +155^{\circ}\text{C}$												
Maximum Working Volt.	200V	250V	350V	250V	250V	350V	350V	350V	500V	500V	500V	500V	500V	500V
Maximum Overload Volt.	400V	500V	700V	500V	500V	700V	700V	700V	1000V	1000V	1000V	1000V	1000V	1000V
Dielectric withstanding Volt.	400V	500V	700V	500V	500V	700V	700V	700V	1000V	1000V	1000V	1000V	1000V	1000V
Value Range	ST	STANDARD $10 \Omega \sim 1 M \Omega$												
±0.5%.±1%	SP	PECIA	L		I	Low to	0.1 Ω	high	to 301	$\operatorname{Meg}\Omega$				
±0.25%						1	l00Ω~	-100K	Ω					
±0.1%	100Ω~47ΚΩ													
±0.170		SPECIAL VALUES AVAILABLE UPON REQUEST												
Temp. Coefficient		:	±10ppr	n/°C 丶	±15pp	om/°C	、±25p	pm/°C	、±50p	opm/°C	、±10	0ppm/°	°C	

Figure 1




METAL FILM FIXED RESISTORS

File No.:	MF-02-D
Version:	А
Page:	4/13
Date :	2021.01.01


5. POWER RATING

(1)**Power Derating** : The rated power at the temperature in excess of 70° C shall be derated in accordance with figure2





(2)Pulse Loading Characteristics





METAL FILM FIXED RESISTORS

(2)Rated Voltage : The DC or AC(rms) continuous working voltage corresponding to the rated power is determined by the following formula:


$$\mathbf{E} = \sqrt{\mathbf{R} \mathbf{x} \mathbf{P}}$$

Where E : Continuous rated DC or AC (rms) working voltage (v)

P: Rated power (w)

R : Resistance value (Ω)


	SYNTON-	TECH CO	RPORATIO		le No.:	MF-02-D			
				v	ersion:	A			
	METAL FI	LM FIXED	RESISTO		nge: ate :	6/13 2021.01.01			
6. DIMENSIONS									
└─── _Н →					O D				
						Unit: m/m			
TYPE	POWER	L	D	Н		Unit: m/m d			
TYPE MF-12	POWER 1/16W 1/6W 1/8W	L	D	Н		d			
		L 3.5 ± 0.3	D 1.8±0.3	H 25 ±					
MF-12	1/16W 1/6W 1/8W					d			
MF-12 MF-25S MF-40S	1/16W 1/6W 1/8W 1/4W 0.4W					d			
MF-12 MF-25S	1/16W 1/6W 1/8W 1/4W	3.5 ± 0.3	1.8±0.3	25 ±	3	d 0.40 ± 0.05			
MF-12 MF-25S MF-40S MF-33S MF-25	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W				3	d			
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W	3.5 ± 0.3	1.8±0.3	25 ±	3	d 0.40 ± 0.05			
MF-12 MF-25S MF-40S MF-33S MF-33S MF-25 MF-50S MF-60S	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W 0.6W	3.5 ± 0.3 6.0 ± 0.5	1.8 ± 0.3 2.3 ± 0.3	25 ± 25 ±	3	$\frac{d}{0.40 \pm 0.05}$ 0.45 ± 0.05			
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-50S MF-60S MF-50	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W 0.6W 1/2W	3.5 ± 0.3	1.8±0.3	25 ±	3	d 0.40 ± 0.05			
MF-12 MF-25S MF-40S MF-33S MF-33S MF-25 MF-50S MF-60S MF-60S MF-50 MF-100S	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W 0.6W 1/2W 1W	3.5 ± 0.3 6.0 ± 0.5 9.0 ± 0.5	1.8 ± 0.3 2.3 ± 0.3 3.2 ± 0.5	25 ± 25 ± 25 ±	3 3 3	$\frac{d}{0.40 \pm 0.05}$ 0.45 ± 0.05 0.5 ± 0.1			
MF-12 MF-25S MF-40S MF-33S MF-33S MF-25 MF-50S MF-60S MF-60S MF-50 MF-100S MF-100	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W 0.6W 1/2W 1W 1W	3.5 ± 0.3 6.0 ± 0.5	1.8 ± 0.3 2.3 ± 0.3	25 ± 25 ±	3 3 3	$\frac{d}{0.40 \pm 0.05}$ 0.45 ± 0.05			
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-50S MF-60S MF-50 MF-100S MF-100 MF-200S	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W 0.6W 1/2W 1W 1W 2W	3.5 ± 0.3 6.0 ± 0.5 9.0 ± 0.5	1.8 ± 0.3 2.3 ± 0.3 3.2 ± 0.5	25 ± 25 ± 25 ±	3 3 3	$\frac{d}{0.40 \pm 0.05}$ 0.45 ± 0.05 0.5 ± 0.1			
MF-12 MF-25S MF-40S MF-33S MF-33S MF-25 MF-50S MF-50S MF-60S MF-60S MF-100S MF-100 MF-100S MF-200S MF-200	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W 0.6W 1/2W 1W 2W 2W 2W 2W	3.5 ± 0.3 6.0 ± 0.5 9.0 ± 0.5 11 ± 1.0	1.8 ± 0.3 2.3 \pm 0.3 3.2 \pm 0.5 4.5 \pm 0.5	25 ± 25 ± 25 ± 35 ±	3 3 3 3	$\frac{d}{0.40 \pm 0.05}$ 0.45 ± 0.05 0.5 ± 0.1 0.65 ± 0.1			
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-50S MF-60S MF-50 MF-100S MF-100 MF-200S	1/16W 1/6W 1/8W 1/4W 0.4W 1/3W 1/4W 1/2W 0.6W 1/2W 1W 1W 2W 2W 3W	3.5 ± 0.3 6.0 ± 0.5 9.0 ± 0.5	1.8 ± 0.3 2.3 ± 0.3 3.2 ± 0.5	25 ± 25 ± 25 ±	3 3 3 3	$\frac{d}{0.40 \pm 0.05}$ 0.45 ± 0.05 0.5 ± 0.1			



Remark : 1. B = 1.15 ~

2. ALTERNATE MARKING METHOD ALSO AVAILABLE ON REQUEST.

Figure4



Remark : 1. $Z = 3 \pm 1$. $K = 2 \pm 0.5$,

2. ALTERNATE MARKING METHOD ALSO AVAILABLE ON REQUEST.

Figure5

	CVN	TON-	TEC		RPOR			e No.:	MF-02-D
	SIN	ION-	IEC		NTUK		10	rsion:	A
	ME	FAL F	ILM F	FIXED	RESI	STOR	$\mathbf{S} = \frac{\mathbf{Pag}}{\mathbf{Da}}$	ge: te :	9/13 2021.01.01
	PE PACH	KING (T	-TYPE)			Da	IC .	2021.01.01
(3) 111	LINCI		I II I 2, I	,	I				
		► D1		_ ←]	\rightarrow				
	<u> </u>	1	—				_		
						P	_		
					± 0.5				
	-		(I			
	_		(_ — I			
			(-			
	_		(_ E	E		
			·····						
				\prec		_ † z	,		
	(1 +								
				5		-			
		\ \		5		_			
				5					
		↓				~ ~			
		↓			. I .				Unit:m/m
TYPE	s IZE	T	Р	W	D1-D2	E	Z	S	Ι
MF-12	SIZE	T 26±1.0		W ±0.5	D1—D2 Max.		Max.	S Max. 1	
MF-12 MF-25S	11		Р ±0.5	W	D1-D2	E Max.		Max.	I Min.
MF-12	SIZE T-26	26±1.0	P ±0.5 5	W ±0.5 6	D1—D2 Max. 0.8	E Max. 1	Max. 1.2	Max.	I Min. 3
MF-12 MF-25S MF-40S MF-33S	SIZE T-26 T-52	26±1.0 52±2.0	P ±0.5 5 5	W ±0.5 6 6	D1—D2 Max. 0.8 0.8	E Max. 1	Max. 1.2 1.2	Max. 1 1	I Min. 3 3
MF-12 MF-258 MF-408 MF-338 MF-25 MF-508	SIZE T-26 T-52 T-26	26±1.0 52±2.0 26±1.0	P ±0.5 5 5 5	W ±0.5 6 6 6	D1—D2 Max. 0.8 0.8 1.0	E Max. 1 1	Max. 1.2 1.2 1.2	Max. 1 1 1	I Min. 3 3 3
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-60S MF-60S MF-50 MF-100S	SIZE T-26 T-52 T-26 T-52	26±1.0 52±2.0 26±1.0 52±2.0	P ±0.5 5 5 5 5 5	$ \begin{array}{c} W \\ \pm 0.5 \\ 6 \\ 6 \\ 6 \\ 6 \\ 6 \end{array} $	D1—D2 Max. 0.8 0.8 1.0 1.0	E Max. 1 1 1 1	Max. 1.2 1.2 1.2 1.2 1.2	Max. 1 1 1 1 1	I Min. 3 3 3 3 3 3 3 3
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-60S MF-50 MF-100S MF-100	SIZE T-26 T-52 T-26 T-52 T-52 T-52 T-52 T-63	26±1.0 52±2.0 26±1.0 52±2.0 52±2.0 52±2.0 63±2.0	$ P \\ \pm 0.5 \\ 5 \\$	$ W \\ \pm 0.5 \\ 6 \\ 6 \\ 6 \\ 6 \\ 6 \\ 6 \\ 6 \\ 6 \\ 6 \\ 6 $	D1-D2 Max. 0.8 0.8 1.0 1.0 1.2 1.2 1.4	E Max. 1 1 1 1 1 1 1 1	Max. 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2	Max. 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	I Min. 3 3 3 3 3 3 3 3 3
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-60S MF-60S MF-50 MF-100S	SIZE T-26 T-52 T-52 T-52 T-52 T-52 T-52 T-52 T-74	26±1.0 52±2.0 26±1.0 52±2.0 52±2.0 52±2.0 63±2.0 74±2.0	P ±0.5 5 5 5 5 5 5 5 5 5 5 5 5	W ±0.5 6 6 6 6 6 6 6 6 6 6	D1—D2 Max. 0.8 0.8 1.0 1.0 1.2 1.2 1.4 1.4	E Max. 1 1 1 1 1 1 1 1 1 1	Max. 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2	Max. 1	I Min. 3 3 3 3 3 3 3 3 3 3 3
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-60S MF-60S MF-50 MF-100S MF-100 MF-200S	SIZE T-26 T-52 T-52	26±1.0 52±2.0 26±1.0 52±2.0 52±2.0 63±2.0 74±2.0 52±2.0	$ P \\ \pm 0.5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 10 \\ $	$ W \\ \pm 0.5 \\ 6 \\$	D1—D2 Max. 0.8 0.8 1.0 1.0 1.2 1.2 1.4 1.4 1.2	E Max. 1 1 1 1 1 1 1 1 1 1 1	Max. 1.2	Max. 1	I Min. 3 3 3 3 3 3 3 3 3 3 3 3
MF-12 MF-25S MF-40S MF-33S MF-25 MF-50S MF-60S MF-60S MF-100S MF-100 MF-100	SIZE T-26 T-52 T-52 T-52 T-52 T-52 T-52 T-52 T-74	26±1.0 52±2.0 26±1.0 52±2.0 52±2.0 52±2.0 63±2.0 74±2.0	P ±0.5 5 5 5 5 5 5 5 5 5 5 5 5	W ±0.5 6 6 6 6 6 6 6 6 6 6	D1—D2 Max. 0.8 0.8 1.0 1.0 1.2 1.2 1.4 1.4	E Max. 1 1 1 1 1 1 1 1 1 1	Max. 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2 1.2	Max. 1	I Min. 3 3 3 3 3 3 3 3 3 3 3



METAL FILM FIXED RESISTORS

 File No.:
 MF-02-D

 Version:
 A

 Page:
 10/13

 Date :
 2021.01.01

7. CHARACTERISTICS

(1) Insulation Resistance

Test Method : Resistors shall be clamped in the trough of a 90 degree metallic V-block, apply DC 100V between this electrode and another lead wire for 1 minute.

Acceptance Standard : 1,000 M ohm above

(2) Terminal Strength

Test Method : Pull a resistor with a weight of 1 kg for 30 seconds. Bend the terminal lead wire with 500gs weight for 90 degree and bend it for 90 degree oppositely and return to normal.

Acceptance Standard : Resistance shall not change more than $\pm 0.2\%$. No evidence of mechanical damage.

(3) Vibration

Test Method : Total amplitude of 1.5mm. The frequency shall vary from 10 HZ to 55 HZ, for approximate 1 second. Make this test in the direction parallel to the resistor axis, and up/down for 2 hours respectively. (altogether 6 hours.)

Acceptance Standard : Resistance shall not change more than $\pm 0.25\%$. No evidence of mechanical damage.

(4) Short Time Overload

Test Method : Resistors shall be tested 2.5 times rated voltage for 5 seconds at ambient room temperature. Acceptance Standard : Resistance shall not change more than ±0.5%.

No evidence of mechanical damage.



METAL FILM FIXED RESISTORS

 File No.:
 MF-02-D

 Version:
 A

 Page:
 11/13

 Date :
 2021.01.01

(5) Load Life

Test Method : Thermostatic chamber at a temperature of $70\pm5^{\circ}$ under a rated DC voltage for 1.5 hours on and 1/2 hour off repeat this cycle for 1000±12 hours.

Acceptance Standard : Resistance shall not change more than $\pm 1.5\%$. No evidence of mechanical damage.

(6) Moisture Resistance

Test Method : At temperature of 40 ± 2 °C and a relative humidity of 90-95% for 1000±12 hours, under a rating DC voltage for hours on and 1/2 hour off.

Acceptance Standard : Resistance shall not change more than ±1%. No evidence of mechanical damage.

(7) Temperature Cycling

Test Method :

STEP	1	2	3	4
TEMP	-55°C	25°C	155°C	25°C
TIME	30min.	10~15min.	30min.	10~15min.

Form 1 to 4 is a cycle as shown above, repeat 5 cycles Measure resistance after 1 hour in normal temperature. Acceptance Standard : Resistance shall not change more than ±0.5%. No evidence of mechanical damage.

(8) Resistance to Soldering Heat

Test Method : Immerse each terminal wire of a resistor up

to 4±0.8mm away from the resistor body

in the solder tank at $350\pm10^{\circ}$ C for 3 ± 0.5 seconds.

Measure resistance in 3 hours.

Acceptance Standard : .Resistance shall not change more than $\pm 0.25\%$.

No evidence of mechanical damage.



METAL FILM FIXED RESISTORS

(9) Resistance to Solvent

Test Method : immerse a resistor completely in reagent at a temperature of $20 \sim 25^{\circ}$ for 30 ± 5 seconds. Acceptance Standard : No evidence of mechanical damage.

(10) Dielectric Withstanding Voltage

Test Method : Resistors shall be clamped in the trough of a 90 degree metallic V-black, apply AC between this electrode and another lead wire for 1 minute. Acceptance Standard : Resistance shall not change more than $\pm 0.5\%$. No evidence of mechanical damage.

(11) Solderability

Test Method : apply flux to the terminal wire of a resistor up to 4±0.8mm away from the resistor body and immerse the flux applied portion in the solder tank at $260\pm5^{\circ}$ C for 3 ± 0.5 seconds

Acceptance Standard : more than 95% of a circumference of the immersed portion shall be completely covered with new solder.

(12) Discontinuous Overload

Test Method : 3 times power rating . 1 second on 25 seconds off cycles 1000 ⁺¹⁰⁰0.

Acceptance Standard : Resistance shall not change more than

 $\pm (0.5\% + 0.05\Omega).$

(13) Soldering Recommendation

Test Method : The Standard Length of epoxy on the terminal of our product is less than 1.5mm. Also, the Standard Welding Point must be over than 1.6mm from Resistor body.

Rated continuous Working Voltage (RCWV) =


power rating x resistance value



SYNTON-TECH CORPORATION METAL FILM FIXED RESISTORS

 $\mathbf{N} \quad \frac{\text{File No.: } MF-02-D}{\text{Version: } A}$ $\mathbf{S} \quad \frac{\text{Page: } 13/13}{\text{Date : } 2021.01.01}$

8. COLOR CODING



Color	1st, 2nd 3rd (Significant Figure)			(Multiplier)	(Tolerance)
Black	0	0	0	10^{0}	
Brown	1	1	1	10 ¹	F (±1%)
Red	2	2	2	10 ²	G (±2%)
Orange	3	3	3	10 ³	
Yellow	4	4	4	104	
Green	5	5	5	10 ⁵	D (±0.5%)
Blue	6	6	6	10 ⁶	C (±0.25%)
Violet	7	7	7	10 ⁷	B (±0.1%)
Gray	8	8	8	10 ⁸	A (±0.05%)
White	9	9	9	109	AA (±0.01%)
Gold				10-1	J (±5%)
Silver				10-2	
Plain				10 ⁻³	—

Figure7